


TIME DELAY SWITCH

DATE:	_	Time Delay Switch
DATE:		Time Delay Switch
PROJECT:		
I OCATION!		

Operating Logic:

Moving the switch to the "on" position turns the light on immediately and the exhaust fan on 15 seconds later.

Both light and fan stay on until the switch is moved to the "off" position which turns the light off immediately and the exhaust fan off after a 1 to 10 minute adjustable delay.



Specifications.

Time Delay:

Fan On Delay: Factory preset @ 15 seconds ± 5 sec.

Fan Off Delay Adjustable: 1 minute

to 10 minutes

Input:

Operating Volts: 120 VAC ± 10%,

50/60 Hz

Power Consumption: 3.5 watts max. (No loads connected)

Output:

Light: 3 amp. resistive @ 120 VAC 500 watt max. incandescent load Fan: 10 amp. resistive, 1/3 hp @ 120 VAC

Mechanical and Hook-up

